


REV-LED COMMERCIAL REPLACEMENT

Owners Manual



Installation Instructions

ALWAYS TURN OFF BREAKER SO NO POWER IS PRESENT AT EQUIPMENT PAD

Step 1:

Remove the old pool light.

Step 2:

Cut light off cord and dispose of light.

Step 3:

Temporarily attach one end of new 100' cord to old cord, pull new cord through to equipment pad.

Step 4:

At pool, REMOVE Protective plastic film

Step 5:

Remove faceplate screw.

Step 6:

Rotate center portion of light counter clockwise while rotating outer faceplate clockwise. This allows removal of light and now have access to center of faceplate to extend the 3 expansion screws which secure it inside the niche.

Step 7:

Place the outer faceplate inside the niche and extend the 3 expansion screws to secure it inside the niche.

Step 8:

Connect the 100' cord to light THROUGH the now installed outer faceplate, using the IP68 connectors.

Step 9:

Insert inner faceplate/light into outer installed faceplate and rotate clockwise to lock into place.

Step 10:

Insert faceplate screw.

Step 11:

In equipment room/pad, Attach other end of the cord to one of the two REV-LED42W 12V Transformer dangling IP68 connectors.

Step 12:

Optional if 120V Light Junction Box is previously powering 120V light. Remove old swimming pool light junction box by disconnecting all wires and by carefully cutting conduit just below old J-box without cutting old cord.

Step 13:

Drill holes in bottom of NM Box to receive conduit adapters (with conduit attached) from lights and power from breaker sub panel.

Step 14:

Install conduit adapter on ends of conduit from light(s) and power from subpanel.

Step 15:

Install NM Box over Conduit adapters with old wires protruding. Secure with PVC cement and locknuts.

Step 16:

Connect 120V cord from transformer to either a switch or timer to turn on/off the REV-LED42W. Otherwise, the breaker would be the only method.

Step 17:

From timer or switch enclosure, there should already be a power cord to power the power supply in Breaker Sub Panel. Install a Single Pole, 15 Amp GFCI breaker.

Step 18:

Turn on GFCI breaker to supply power to REV 12V Transformer.

Step 19:

Reset timer if necessary. The light is now ready to use.

Warranty

Your new REV-LED Light and power adapter is warranted for a period of 12 months, Lights for a period of 36 months.

This warranty is nontransferable and extends only to the original retail buyer and only during the time in which the original retail buyer occupies the site where the product was originally installed.

This warranty applies to products used in swimming pools, spas, & aquaculture applications only and does not apply to any product which has been subjected to negligence, alteration, accident, abuse, misuse, improper installation, abrasives, corrosion, improper voltage supply, vandalism, civil disturbances, or acts of God (including but not limited to damage caused by freezing, lightning strikes, and other damage caused by catastrophic events). The only warranties authorized by CMI are those set forth herein. CMI does not authorize other persons to extend any warranties with respect to its products, nor will CMI assume liability for any unauthorized warranties made in connection with the sale of its products. CMI will not be responsible for any statements that are made or published, written or oral, which are misleading or inconsistent with the facts as published in the literature or specifications furnished by CMI.

Warranty Claim Procedure

To be eligible of the benefits of this warranty, the consumer must contact the installer/seller, builder, dealer, or retailer (point of purchase) or the CMI pool products distributor in your area as soon as the defect occurs and make sure that the product does not deteriorate further. The consumer must have proof of purchase. Any product returned or repaired without prior authorization of CMI will be refused. All equipment must be inspected by a local CMI authorized representative or at the factory before warranty is authorized. All charges or expenses for freight to and from the factory, removal and reinstallation of the products, or installation of a replacement product are the responsibility of the purchaser unless otherwise expressly authorized in writing by CMI. CMI, at its discretion, may repair or replace free of charge any product that proves defective within the warranty period, or it may issue credit in the amount of the invoice of the defective product in lieu of its repair or replacement. CMI reserves its right to substitute new or improved product on any replacements.

Thank you for your purchase and enjoy safe lights in your pool & spa.

We hope you enjoy and tell your friends! For questions or additional product information, please visit our website at www.CMIWebsite.com or contact our Smart Lighting Team via info@cmiwebsite.com.

